

H^∞ Performance of Interval Systems

Long Wang*

Center for Systems and Control, Department of Mechanics and Engineering Science,
Peking University, Beijing 100871, CHINA

Abstract

In this paper, we study H^∞ performance of interval systems. We prove that, for an interval system, the maximal H^∞ norm of its sensitivity function is achieved at twelve (out of sixteen) Kharitonov vertices.

Keywords: H^∞ Control Theory, Uncertain Systems, Performance Analysis, Robustness, Interval Model, Sensitivity Functions.

1 Introduction

Motivated by the seminal theorem of Kharitonov on robust stability of interval polynomials[1, 2], a number of papers on robustness analysis of uncertain systems have been published in the past few years[3, 4, 5, 6, 7, 8, 9, 10]. Kharitonov's theorem states that the Hurwitz stability of the real (or complex) interval polynomial family can be guaranteed by the Hurwitz stability of four (or eight) prescribed critical vertex polynomials in this family. This result is significant since it reduces checking stability of infinitely many polynomials to checking stability of finitely many polynomials, and the number of critical vertex polynomials need to be checked is independent of the order of the polynomial family. An important extension of Kharitonov's theorem is the edge theorem discovered by Bartlett, Hollot and Huang[4]. The edge theorem states that the stability of a polytope of polynomials can be guaranteed by the stability of its one-dimensional exposed edge polynomials. The significance of the edge theorem is that it allows some (affine) dependency among polynomial coefficients, and applies to more general stability regions, e.g., unit circle, left sector, shifted half plane, hyperbola region, etc. When the dependency among polynomial coefficients is nonlinear, however, Ackermann shows that checking a subset of a polynomial family generally can not guarantee the stability of the entire family[11, 12].

In this paper, we prove that, for an interval system, the maximal H_∞ norm of its sensitivity function is achieved at twelve (out of sixteen) Kharitonov vertices. This

*Supported by National Natural Science Foundation of China (69925307), National Key Basic Research Special Fund (No. G1998020302) and the Research Fund for the Doctoral Program of Higher Education.

result is useful in robust performance analysis and H_∞ control design for dynamic systems under parametric perturbations.

2 Main Results

Denote the m -th, n -th ($m < n$) order real interval polynomial families $K_g(s)$, $K_f(s)$ as

$$K_g(s) = \{g(s) | g(s) = \sum_{i=0}^m b_i s^i, b_i \in [\underline{b}_i, \overline{b}_i], i = 0, 1, \dots, m\}, \quad (1)$$

$$K_f(s) = \{f(s) | f(s) = \sum_{i=0}^n a_i s^i, a_i \in [\underline{a}_i, \overline{a}_i], i = 0, 1, \dots, n\}. \quad (2)$$

For any $f(s) \in K_f(s)$, it can be expressed as

$$f(s) = \alpha_f(s^2) + s\beta_f(s^2), \quad (3)$$

where

$$\alpha_f(s^2) = a_0 + a_2 s^2 + a_4 s^4 + a_6 s^6 + \dots, \quad (4)$$

$$\beta_f(s^2) = a_1 + a_3 s^2 + a_5 s^4 + a_7 s^6 + \dots \quad (5)$$

Obviously, for any fixed $\omega \in R$, $\alpha_f(-\omega^2)$ and $\omega\beta_f(-\omega^2)$ are the real and imaginary parts of $f(j\omega) \in C$ respectively.

For the interval polynomial family $K_f(s)$, define

$$\alpha_f^{(1)}(s^2) = \underline{a}_0 + \overline{a}_2 s^2 + \underline{a}_4 s^4 + \overline{a}_6 s^6 + \dots, \quad (6)$$

$$\alpha_f^{(2)}(s^2) = \overline{a}_0 + \underline{a}_2 s^2 + \overline{a}_4 s^4 + \underline{a}_6 s^6 + \dots, \quad (7)$$

$$\beta_f^{(1)}(s^2) = \underline{a}_1 + \overline{a}_3 s^2 + \underline{a}_5 s^4 + \overline{a}_7 s^6 + \dots, \quad (8)$$

$$\beta_f^{(2)}(s^2) = \overline{a}_1 + \underline{a}_3 s^2 + \overline{a}_5 s^4 + \underline{a}_7 s^6 + \dots, \quad (9)$$

and denote the four Kharitonov vertex polynomials of $K_f(s)$ as

$$f_{ij}(s) = \alpha_f^{(i)}(s^2) + s\beta_f^{(j)}(s^2), \quad i, j = 1, 2 \quad (10)$$

For the interval polynomial family $K_g(s)$, the corresponding $\alpha_g^{(i)}(s)$, $\beta_g^{(j)}(s)$ and $g_{ij}(s) \in K_g(s)$ can be defined analogously.

Denote by H the set of all Hurwitz stable polynomials (i.e. all of their roots lie within the open left half of the complex plane).

For the proper stable rational function $\frac{p(s)}{q(s)}$, the H_∞ norm is defined as

$$\left\| \frac{p(s)}{q(s)} \right\|_{\infty} = \sup \left\{ \left| \frac{p(j\omega)}{q(j\omega)} \right| \mid \omega \in (-\infty, +\infty) \right\} \quad (11)$$

The proper complex rational function $\frac{p(s)}{q(s)}$ is said to be strictly positive real, if 1) $q(s) \in H$; and 2) for any $\omega \in R$, $\Re \frac{p(j\omega)}{q(j\omega)} > 0$.

Denote by SPR the set of all strictly positive real rational functions.

Lemma 2.1[14]

For any fixed $\omega \in R$, $f(s) \in K_f(s)$, we have

$$\alpha_f^{(1)}(-\omega^2) \leq \alpha_f(-\omega^2) \leq \alpha_f^{(2)}(-\omega^2), \quad (12)$$

$$\beta_f^{(1)}(-\omega^2) \leq \beta_f(-\omega^2) \leq \beta_f^{(2)}(-\omega^2). \quad (13)$$

Lemma 2.2[11] (Zero Exclusion Principle)

For the n -th order polynomial family

$$f(s, T) =: \{f(s, t) \mid t \in T\}, \quad (14)$$

where T is a bounded connected closed set, and the coefficients of $f(s, t)$ are continuous functions of t , then $f(s, T) \in H$ if and only if

- 1) there exists $t^* \in T$, such that $f(s, t^*) \in H$;
- 2) $0 \notin f(j\omega, T)$, $\forall \omega \in R$.

Consider the strictly proper open-loop transfer function

$$P = \frac{g(s)}{f(s)} \quad (15)$$

and suppose the closed-loop system is stable under negative unity feedback. Denote its sensitivity function as

$$S = \frac{1}{1+P} = \frac{f(s)}{f(s) + g(s)} \quad (16)$$

Apparently, we have

$$\|S\|_{\infty} \geq 1 \quad (17)$$

For notational simplicity, define

$$J_{i_1 j_1 i_2 j_2}(s) = g_{i_1 j_1}(s) + (1 + \delta e^{j\theta}) f_{i_2 j_2}(s), \quad \delta \in (0, 1), \quad i_1, j_1, i_2, j_2 = 1, 2, \quad \theta \in [-\pi, \pi]. \quad (18)$$

Lemma 2.3

Suppose $g(s) + f(s) \in H$. Then, for any $\gamma > 1$, we have

$$\|S\|_{\infty} < \gamma \iff g(s) + (1 + \frac{1}{\gamma} e^{j\theta}) f(s) \in H, \quad \forall \theta \in [-\pi, \pi]. \quad (19)$$

Proof: Necessity: Since $g(s) + f(s) \in H$ and $\|\frac{\frac{1}{\gamma}f(s)}{f(s)+g(s)}\|_\infty < 1$, by Rouché's Theorem, we know that

$$[g(s) + f(s)] + \frac{1}{\gamma}e^{j\theta}f(s) \in H, \quad \forall \theta \in [-\pi, \pi] \quad (20)$$

Sufficiency: Now suppose on the contrary that $\|S\|_\infty \geq \gamma$, namely, $\|\frac{\frac{1}{\gamma}f(s)}{f(s)+g(s)}\|_\infty \geq$

1. Since $|\frac{\frac{1}{\gamma}f(s)}{f(s)+g(s)}|_{s=j\omega}$ is a continuous function of ω , and since

$$\lim_{\omega \rightarrow \infty} |\frac{\frac{1}{\gamma}f(s)}{f(s)+g(s)}|_{s=j\omega} = \frac{1}{\gamma} < 1 \quad (21)$$

there must exist ω_0 such that

$$|\frac{\frac{1}{\gamma}f(s)}{f(s)+g(s)}|_{s=j\omega_0} = 1 \quad (22)$$

Therefore, there exists $\theta_0 \in [-\pi, \pi]$ such that

$$\{g(s) + f(s) + \frac{1}{\gamma}e^{j\theta_0}f(s)\}_{s=j\omega_0} = 0 \quad (23)$$

which contradicts the original hypothesis. This completes the proof.

Lemma 2.4

For any $\delta \in (0, 1)$, $\theta \in [-\pi, \pi]$, we have

$$W(s) =: \{g(s) + (1 + \delta e^{j\theta})f(s) | g(s) \in K_g(s), f(s) \in K_f(s)\} \subset H \iff \quad (24)$$

$$J_{1111}, J_{1212}, J_{2222}, J_{2121}, J_{1112}, J_{1222}, J_{2221}, J_{2111}, J_{1211}, J_{2212}, J_{2122}, J_{1121} \in H \quad (25)$$

Proof: Necessity is obvious. To prove sufficiency, note that $W(s)$ is a set of polynomials with complex coefficients, and with constant order n . By Lemma 2.2, it suffices to show that

$$0 \notin W(j\omega), \quad \forall \omega \in R \quad (26)$$

Since $0 \notin W(j\omega_\infty)$ for sufficiently large ω_∞ , we only need to show that

$$0 \notin \partial W(j\omega), \quad \forall \omega \in R \quad (27)$$

where $\partial W(j\omega)$ stands for the boundary of $W(j\omega)$ in the complex plane.

To construct $\partial W(j\omega)$, note that $\arg(1 + \delta e^{j\theta}) \in (-\frac{\pi}{2}, \frac{\pi}{2})$. Suppose now $\omega \geq 0$ and $\arg(1 + \delta e^{j\theta}) \in [0, \frac{\pi}{2})$. Then by Lemma 2.1, we know that $K_g(j\omega), K_f(j\omega)$ are rectangles with edges parallel to the coordinate axes. The four vertices of $K_g(j\omega)$ are $g_{11}(j\omega), g_{12}(j\omega), g_{21}(j\omega), g_{22}(j\omega)$, respectively; and the four vertices of $K_f(j\omega)$ are $f_{11}(j\omega), f_{12}(j\omega), f_{21}(j\omega), f_{22}(j\omega)$, respectively. $(1 + \delta e^{j\theta})K_f(j\omega)$ is generated by rotating $K_f(j\omega)$ by $\arg(1 + \delta e^{j\theta})$ counterclockwisely, and then scaling by

$|1 + \delta e^{j\theta}|$. Thus, $W(j\omega) = K_g(j\omega) + (1 + \delta e^{j\theta})K_f(j\omega)$ is a convex polygon with eight edges. These edges are parallel to either the edges of $K_g(j\omega)$ or the edges of $(1 + \delta e^{j\theta})K_f(j\omega)$. Therefore, their orientations are fixed (independent of ω). The eight vertices of $W(j\omega)$ are (clockwisely) $J_{1111}(j\omega)$, $J_{1112}(j\omega)$, $J_{1212}(j\omega)$, $J_{1222}(j\omega)$, $J_{2222}(j\omega)$, $J_{2121}(j\omega)$, $J_{2111}(j\omega)$, respectively.

Now suppose on the contrary that there exists $\omega_0 \geq 0$ such that

$$0 \in \partial W(j\omega_0) \quad (28)$$

Without loss of generality, suppose

$$0 \in \{\lambda J_{1111}(j\omega_0) + (1 - \lambda)J_{1112}(j\omega_0) | \lambda \in [0, 1]\} \quad (29)$$

Namely, there exists $\lambda_0 \in (0, 1)$ such that

$$\lambda_0 J_{1111}(j\omega_0) + (1 - \lambda_0)J_{1112}(j\omega_0) = 0 \quad (30)$$

Since $J_{1111}(s), J_{1112}(s) \in H$, we have

$$\frac{d}{d\omega} \arg J_{1111}(j\omega) > 0, \quad \frac{d}{d\omega} \arg J_{1112}(j\omega) > 0 \quad (31)$$

Thus[15]

$$\frac{d}{d\omega} \arg[J_{1112}(j\omega) - J_{1111}(j\omega)]|_{\omega=\omega_0} = \quad (32)$$

$$(1 - \lambda_0) \frac{d}{d\omega} \arg J_{1111}(j\omega)|_{\omega=\omega_0} + \lambda_0 \frac{d}{d\omega} \arg J_{1112}(j\omega)|_{\omega=\omega_0} > 0 \quad (33)$$

This contradicts the fact that the edges of $W(j\omega)$ have fixed orientations. Thus

$$0 \notin \partial W(j\omega) \quad (34)$$

Suppose now $\omega \leq 0$ and $\arg(1 + \delta e^{j\theta}) \in (-\frac{\pi}{2}, 0]$. Then $K_g(j\omega), (1 + \delta e^{j\theta})K_f(j\omega)$ are the mirror images (with respect to the real axis) of the corresponding sets in the case of $\omega \geq 0$ and $\arg(1 + \delta e^{j\theta}) \in [0, \frac{\pi}{2})$. Therefore, following an identical line of arguments, we have

$$0 \notin \partial W(j\omega) \quad (35)$$

The cases when $\omega \geq 0$ and $\arg(1 + \delta e^{j\theta}) \in (-\frac{\pi}{2}, 0]$ and when $\omega \leq 0$ and $\arg(1 + \delta e^{j\theta}) \in [0, \frac{\pi}{2})$ are also symmetric with respect to the real axis. Hence, we only need to consider the former case. In this case, $K_g(j\omega), K_f(j\omega)$ are rectangles with edges parallel to the coordinate axes. $(1 + \delta e^{j\theta})K_f(j\omega)$ is generated by rotating $K_f(j\omega)$ by $|\arg(1 + \delta e^{j\theta})|$ clockwise, and then scaling by $|1 + \delta e^{j\theta}|$. Thus, $W(j\omega) = K_g(j\omega) + (1 + \delta e^{j\theta})K_f(j\omega)$ is a convex polygon with eight edges. These edges are parallel to either the edges of $K_g(j\omega)$ or the edges of $(1 + \delta e^{j\theta})K_f(j\omega)$. Therefore, their orientations are fixed (independent of ω). The eight vertices of $W(j\omega)$ are (clockwisely) $J_{1111}(j\omega)$, $J_{1211}(j\omega)$, $J_{1212}(j\omega)$, $J_{2212}(j\omega)$, $J_{2222}(j\omega)$, $J_{2122}(j\omega)$, $J_{2121}(j\omega)$, $J_{1121}(j\omega)$, respectively. Thus, following a similar argument, we have

$$0 \notin \partial W(j\omega) \quad (36)$$

This completes the proof.

The following theorem shows that, for an interval system, the maximal H_∞ norm of its sensitivity function is achieved at twelve (out of sixteen) Kharitonov vertices.

Theorem 2.1

Suppose $g_{ij}(s) + f_{ij}(s) \in H$, $i, j = 1, 2$. Then

$$\max\{\|\frac{f(s)}{f(s) + g(s)}\|_\infty | g(s) \in K_g(s), f(s) \in K_f(s)\} = \quad (37)$$

$$\max\{\|\frac{f_{i_2j_2}(s)}{f_{i_2j_2}(s) + g_{i_1j_1}(s)}\|_\infty | (i_1j_1i_2j_2) = (1111), (1212), \quad (38)$$

$$(2222), (2121), (1112), (1222), (2221), (2111), (1211), (2212), (2122), (1121)\} \quad (39)$$

Proof: Since $g_{ij}(s) + f_{ij}(s) \in H$, $i, j = 1, 2$, by Kharitonov's Theorem[1], we know that $K_g(s) + K_f(s) \subset H$. Let

$$\gamma_1 = \max\{\|\frac{f(s)}{f(s) + g(s)}\|_\infty | g(s) \in K_g(s), f(s) \in K_f(s)\} \quad (40)$$

$$\gamma_2 = \max\{\|\frac{f_{i_2j_2}(s)}{f_{i_2j_2}(s) + g_{i_1j_1}(s)}\|_\infty | (i_1j_1i_2j_2) = (1111), (1212), \quad (41)$$

$$(2222), (2121), (1112), (1222), (2221), (2111), (1211), (2212), (2122), (1121)\} \quad (42)$$

Then apparently

$$\gamma_1 \geq \gamma_2 \geq 1 \quad (43)$$

Now suppose $\gamma_1 \neq \gamma_2$, namely, $\gamma_1 > \gamma_2$. Then there exists γ_0 such that $\gamma_1 > \gamma_0 > \gamma_2$. Thus, for any $(i_1j_1i_2j_2) \in \{(1111), (1212), (2222), (2121), (1112), (1222), (2221), (2111), (1211), (2212), (2122), (1121)\}$, we have

$$\|\frac{f_{i_2j_2}(s)}{f_{i_2j_2}(s) + g_{i_1j_1}(s)}\|_\infty < \gamma_0 \quad (44)$$

Hence, by Lemma 2.3, we have

$$g_{i_1j_1}(s) + (1 + \frac{1}{\gamma_0}e^{j\theta})f_{i_2j_2}(s) \in H, \quad \forall \theta \in [-\pi, \pi] \quad (45)$$

By Lemma 2.4, we know that

$$\{g(s) + (1 + \frac{1}{\gamma_0}e^{j\theta})f(s) | g(s) \in K_g(s), f(s) \in K_f(s)\} \subset H, \quad \forall \theta \in [-\pi, \pi] \quad (46)$$

Therefore, by Lemma 2.3, for any $g(s) \in K_g(s), f(s) \in K_f(s)$, we have

$$\|\frac{f(s)}{f(s) + g(s)}\|_\infty < \gamma_0 \quad (47)$$

Namely

$$\max\{\|\frac{f(s)}{f(s) + g(s)}\|_\infty | g(s) \in K_g(s), f(s) \in K_f(s)\} < \gamma_0 \quad (48)$$

That is, $\gamma_1 < \gamma_0$, which contradicts $\gamma_1 > \gamma_0 > \gamma_2$. This completes the proof.

3 Conclusions

We have proved that, for an interval system, the maximal H^∞ norm of its sensitivity function is achieved at twelve (out of sixteen) Kharitonov vertices. This result is useful in robust performance analysis and H_∞ control design for dynamic systems under parametric perturbations.

References

- [1] V.L.Kharitonov. Asymptotic stability of an equilibrium position of a family of systems of linear differential equations, *Differential'nye Uravneniya*, vol.14, 2086-2088, 1978.
- [2] V.L.Kharitonov. The Routh-Hurwitz problem for families of polynomials and quasipolynomials, *Izvetiy Akademii Nauk Kazakhskoi SSR, Seria fizikomatematicheskaya*, vol.26, 69-79, 1979.
- [3] C.V.Hollot and R.Tempo. On the Nyquist envelope of an interval plant family, *IEEE Trans. on Automatic Control*, vol.39, 391-396, 1994.
- [4] A.C.Bartlett, C.V.Hollot and L.Huang. Root locations of an entire polytope of polynomials: It suffices to check the edges, *Mathematics of Control, Signals, and Systems*, vol.1, 61-71, 1988.
- [5] M.Fu and B.R.Barmish. Polytope of polynomials with zeros in a prescribed set, *IEEE Trans. on Automatic Control*, vol.34, 544-546, 1989.
- [6] L. Wang and L. Huang. Vertex results for uncertain systems, *Int. J. Systems Science*, vol.25, 541-549, 1994.
- [7] L. Wang and L. Huang. Extreme point results for strict positive realness of transfer function families, *Systems Science and Mathematical Sciences*, vol.7, 371-378, 1994.
- [8] B. R. Barmish, C. V. Hollot, F. J. Kraus and R. Tempo. Extreme point results for robust stabilization of interval plants with first order compensators, *IEEE Trans. on Automatic Control*, vol.37, 707-714, 1992.

- [9] H. Chapellat, M. Dahleh and S. P. Bhattacharyya. On robust nonlinear stability of interval control systems, IEEE Trans. on Automatic Control, vol.36, 59-67, 1991.
- [10] L. Wang and L. Huang. Finite verification of strict positive realness of interval rational functions, Chinese Science Bulletin, vol.36, 262-264, 1991.
- [11] J.Ackermann. Uncertainty structures and robust stability analysis, Proc. of European Control Conference, 2318-2327,1991.
- [12] J.Ackermann. Does it suffice to check a subset of multilinear parameters in robustness analysis? IEEE Trans. on Automatic Control, vol.37, 487-488, 1992.
- [13] L.Wang, On strict positive realness of multilinearly parametrized interval systems, Proceedings of the 1st Chinese Control Conference, Taiyuan, China, 1994.
- [14] S. Dasgupta. Kharitonov's theorem revisited, Systems and Control Letters, vol.11, No.4, 381-384, 1988.
- [15] A.Rantzer. Stability conditions for polytopes of polynomials, IEEE Trans. on Automatic Control, vol.37, 79-89, 1992.
- [16] L.A.Zadeh and C.A.Desoer, Linear System Theory: A State Space Approach, McGraw-Hill, New York, 1963.
- [17] J.Ackermann et al., Robust Control: Systems with Uncertain Physical Parameters, Springer-Verlag, Berlin, 1994.
- [18] B.R.Barmish, New tools for robustness analysis, Proc. of IEEE Conf. on Decision and Control, 1-6, 1988.